

A. ~~A.~~ Introduction

1. **Title:** Power System Stabilizer (PSS)
2. **Number:** VAR-501-WECC-~~3.14~~
3. **Purpose:** To ensure the Western Interconnection is operated in a coordinated manner under normal and abnormal conditions by establishing the performance criteria for WECC power system stabilizers.
4. **Applicability:**
 - 4.1 Generator Operator
 - 4.2 Generator Owner
5. **Facilities:** This standard applies to synchronous generators, connected to the Bulk Electric System, ~~that meet~~meeting the definition of Commercial Operation.
6. **Effective Date:** ~~The first day of the first quarter following regulatory approval, except for Requirement R3.~~

~~For units placed in first time service after regulatory approval, Requirement R3 is effective the first day of the first quarter following final regulatory approval.~~

~~For units placed in service prior to final regulatory approval, Requirement R3 is effective the first day of the first quarter that is five years after regulatory approval.~~

~~B.~~

B. Requirements and Measures

- R1. Each Generator Owner shall provide to its Transmission Operator, the Generator Owner's written Operating Procedure or other document(s) describing those known circumstances during which the Generator Owner's PSS will not be providing an active signal to the Automatic Voltage Regulator (AVR), within 180 days of any of the following events: *[Violation Risk Factor: Low] [Time Horizon: Planning Horizon]*
 - The effective date of this standard;
 - The PSS's Commercial Operation date; or
 - Any changes to the PSS operating specifications.
- M1. Each Generator Owner will have documented evidence that it provided to its Transmission Operator, within the time allotted as described in the procedures required under Requirement R1, written Operating Procedures or other document(s) describing those known circumstances during which the Generator Owner's PSS will not be providing an active signal to the AVR.

For auditing purposes, because Requirement R1 conditions are intended to be unchanged unless the Transmission Operator is otherwise notified, the Generator Owner only needs to provide the documentation to the Transmission Operator one time, or whenever the operating specifications change.

For auditing purposes, if a PSS is in service but is not providing an active signal to the AVR as described in Requirement R1, the disabled period does not count against the Requirement R2 mandate to be in service except as otherwise allowed.

- R2.** Each Generator Operator shall have its PSS in service while synchronized, except during any of the following: *[Violation Risk Factor: Medium] [Time Horizon: Operating Assessment]*

- Component failure
- Testing of a Bulk Electric System Element affecting or affected by the PSS
- Maintenance
- As agreed upon by the Generator Operator and the Transmission Operator

A PSS that is out of service for less than 30 minutes does not create a violation of this Requirement, regardless of cause.

- M2.** Each Generator Operator will have documentation of each claimed exception specified in Requirement R2. Documentation may include, but is not limited to:

- A written explanation covering the bulleted exception that describes the circumstances of the exception as allowed in Requirement R2.
- Documented evidence that the Generator Operator and the Transmission Operator agreed the PSS would not be operating during a specified set of circumstances, where the exception is claimed under the last bullet of Requirement R2.

For auditing purposes, the presumption is that the PSS was in service unless otherwise exempted in Requirement R2. Evidence need only be provided to prove the circumstances during which the PSS was not in service for periods in excess of 30 minutes.

- R3.** Each Generator Owner shall tune its PSS to meet the following inter-area mode criteria, except as specified in Requirement R3, Part 3.5 below: *[Violation Risk Factor: Medium] [Time Horizon: Operating Assessment]*

- 3.1.** PSS shall be set to provide the measured, simulated, or calculated compensated V_t/V_{ref} frequency response of the excitation system and synchronous machine such that the phase angle will not exceed ± 30 degrees through the frequency range from 0.2 Hertz to the lesser of 1.0 Hertz or the highest frequency at which the phase of the V_t/V_{ref} frequency response does not exceed 90 degrees.
- 3.2.** PSS output limits shall be set to provide at least $\pm 5\%$ of the synchronous machine's nominal terminal voltage.
- 3.3.** PSS gain shall be set to between $1/3$ and $1/2$ of maximum practical gain.
- 3.4.** PSS washout time constant shall be no greater than 30 seconds.

3.5. Units that have an excitation system or PSS that is incapable of meeting the tuning requirements of Requirement R3 are exempt from Requirement R3 until the voltage regulator is either replaced or retrofitted such that the PSS becomes capable of meeting the tuning requirements.

M3. Each Generator Owner will have documented evidence that its PSS was tuned to meet the specifications of Requirement R3.

If the exception under Requirement R3, Part 3.5, is claimed, the Generator Owner will have documented evidence describing: 1) the conditions that render the PSS incapable of meeting the tuning requirements, and 2) the date the voltage regulator was last replaced or retrofitted.

R4. Each Generator Owner shall install and complete start-up testing of a PSS on its generator within 180 days of either of the following events: *[Violation Risk Factor: Medium] [Time Horizon: Operational Assessment]*

- The Generator Owner connects a generator to the BES, after achieving Commercial Operation, and after the Effective Date of this standard.
- The Generator Owner replaces the voltage regulator on its existing excitation system, after achieving Commercial Operation for its generator that is connected to the BES, and after the Effective Date of this standard.

M4. Each Generator Owner will have evidence that it installed and completed start-up testing of a PSS on its generator within 180 days of either of the conditions described in Requirement R4, and when those conditions occur after the Effective Date of this standard.

~~For auditing purposes~~ The first bullet of Requirement R4, ~~bullet one~~ only applies to equipment on its initial (first energization) connection to the BES.

R5. Each Generator Owner shall repair or replace a PSS within 24 months of that PSS becoming incapable of meeting the tuning specifications stated in Requirement R3. *[Violation Risk Factor: Medium] [Time Horizon: Operational Assessment]*

M5. Each Generator Owner will have evidence that it repaired or replaced its PSS within 24 months of that PSS becoming incapable of meeting the tuning specifications of Requirement R3. Evidence may include, but is not limited to, documentation of the date the PSS became incapable of meeting the Requirement R3 tuning specifications, and the date the PSS was returned to service, demonstrating that the span of time between the two events was less than 24 months.

~~C. Compliance~~**~~C. Compliance~~****~~1. Compliance Monitoring Process~~****~~1.1 Compliance Enforcement Authority~~**

~~：“Compliance Enforcement Authority” means NERC or the Regional Entity, or any entity as otherwise designated by an Applicable Governmental Authority, in their respective roles of monitoring and/or enforcing compliance with mandatory and enforceable Reliability Standards in their respective jurisdictions.~~

~~1.2 Compliance Monitoring and Assessment Processes~~

- ~~• Compliance Audits~~
- ~~• Self-Certifications~~
- ~~• Spot-Checking~~
- ~~• Compliance Investigations~~
- ~~• Self-Reporting~~
- ~~• Complaints~~

~~1.3 Evidence Retention~~

~~：The following evidence retention ~~periods~~period(s) identify the period of time an entity is required to retain specific evidence to demonstrate compliance. For instances where the evidence retention period specified below is shorter than the time since the last audit, the Compliance Enforcement Authority may ask an entity to provide other evidence to show that it was compliant for the full time period since the last audit.~~

~~The applicable entity shall keep data or evidence to show compliance as identified below unless directed by its Compliance Enforcement Authority to retain specific evidence for a longer period of time as part of an investigation.~~

- ~~• Each Generator Operator shall keep evidence for all Requirements of the document for a period of three years plus calendar current.~~

~~1.4 Additional Compliance Information~~

~~None~~

~~D. Regional Differences~~

~~None~~

Table of Compliance Elements

~~**1.3 Compliance Monitoring and Enforcement Program:** As defined in the NERC Rules of Procedure, “Compliance Monitoring and Enforcement Program” refers to the identification of the processes that will be used to evaluate data or information for the purpose of assessing performance or outcomes with the associated Reliability Standard.~~

VAR-501-WECC-~~43.1~~ – Power System Stabilizer

R	Violation Severity Levels			
	Lower VSL	Moderate VSL	High VSL	Severe VSL
R1	NA	NA	NA	The Generator Owner failed to provide its PSS operating specifications to the Transmission Operator as required in Requirement R1.
R2	Each Generator Operator not having its PSS in service while synchronized in accordance with Requirement R2, for more than 30 minutes but less than 60 minutes.	Each Generator Operator not having its PSS in service while synchronized in accordance with Requirement R2, for more than 60 minutes but less than 120 minutes.	Each Generator Operator not having its PSS in service while synchronized in accordance with Requirement R2, for more than 120 minutes but less than 180 minutes.	Each Generator Operator not having its PSS in service while synchronized in accordance with Requirement R2, for more than 180 minutes.
R3	The Generator Owner's PSS failed to meet any of the required performances in Requirement R3, two times or fewer during the audit period.	The Generator Owner's PSS failed to meet any of the required performances in Requirement R3, three times during the audit period.	The Generator Owner's PSS failed to meet any of the required performances in Requirement R3, four times during the audit period.	The Generator Owner's PSS failed to meet any of the required performances in Requirement R3, five times or more during the audit period.
R4	NA	NA	NA	The Generator Owner failed to install on its generator a PSS, as required in Requirement R4.
R5	NA	NA	NA	The Generator Owner failed to repair or replace a non-operational PSS as required in Requirement R5.

VAR-501-WECC-~~43.1~~— Power System Stabilizer

VAR-501-WECC-~~3.14~~ – Power System Stabilizer

D. Regional VariancesNone.**E. Associated Documents**None.**Version History**

Version	Date	Action	Change Tracking
1	April 16, 2008	Permanent Replacement Standard for VAR-STD-002b-1	
1	October 28, 2008	Adopted by NERC Board of Trustees	
1	April 21, 2011	FERC Order issued approving VAR-501-WECC-1 (FERC approval effective June 27, 2011; Effective Date July 1, 2011)	
2	November 13, 2014	Adopted by NERC Board of Trustees	
2	March 3, 2015	FERC letter order approved VAR-501-WECC-2	
3	February 9, 2017	Adopted by NERC Board of Trustees	
3	April 28, 2017	FERC letter order approved VAR-501-WECC-3	
<u>3.1</u>	<u>August 10, 2017</u>	<u>Adopted by the NERC Board of Trustees</u>	<u>Errata</u>
3.1	TBD <u>September 26, 2017</u>	TBD <u>FERC letter order issued approving VAR-501-WECC-3.1</u>	
<u>4</u>	<u>December 6, 2022</u>	<u>WECC Standards Committee accepted a “no change “ recommendation followed by</u>	<u>Non-substantive changes were approved by the</u>

VAR-501-WECC-~~3.14~~ – Power System Stabilizer

		<u>an information-only filing to NERC.</u>	<u>WECC Standards Committee as allowed in the WECC Reliability Standards Development Procedures. An information-only filing provided to NERC reflects the following: 1) updates to the template and syntax, 2) removal of stale-dated language from the Effective Date, 3) deletion of “For auditing purposes of...” from M4, 4) in the Guidance section, “dampen” was replaced with “damp”, and syntax was addressed deleting “still”, “of those”, “of the”, and “to ensure” was replaced with “ensuring”, and “wash out” was replaced with “washout.”</u>
--	--	--	---

VAR-501-WECC-3.14 – Power System Stabilizer

~~Guideline and Technical Basis~~

~~PSS systems are used to minimize real power oscillations by rapidly adjusting the field of the generator to dampendamp the low frequency oscillations.~~

~~It is necessary for large numbers of PSS devices to be in operation in the Western Interconnection to provide the required system damping while still allowing for some of these units to be out of service whenever necessary.~~

~~Mandate to Install a PSS~~

~~Nothing in this Regional Reliability Standard (RSS) should be construed to require installation of a PSS solely because a PSS is not currently installed as of the Effective Date of this RRS. Rather, installation is only mandated on the occurrence of either of the triggering eventevent described in Requirement R4, Bullet 1 or Bullet 2, after the Effective Date of the RRS.~~

~~It should be noted that a PSS is neither Transmission nor generation.~~

~~Requirement R1~~

~~Requirement R1 addresses normal operating conditions.~~

~~Requirement R1 recognizes that PSS systems have varying states, such as on, off, active, and non active. As long as the PSS is operating in accordance with the documentation provided to the Transmission Operator, this is not considered a status change for purposes of this standardStandard.~~

~~This Requirement eliminates the requirement to count hours as required in the previous version of this standardStandard while also allowing the Generator Owner to create a unit specific operating plan.~~

~~The intent of Requirement R1 is to provide the Transmission Operator, the PSS operating zone in which the PSS is “active” providing damping to the power system. Some PSS may be programmed to become “active” at a specified megawatt loading level and above while others may be programmed to be “active” in a particular band of megawatt loading levels and are “non active” only when passing through the “rough zone” or some other band. A “rough zone” is a megawatt loading band in which the generator turbine system could contribute to system instability.~~

~~Requirement R2~~

~~This Requirement only applies when the PSS is out of service for a period greater than 30 minutes.~~

~~Unlike Requirement R1, Requirement R2 addresses exceptions to normal operation.~~

VAR-501-WECC-3.14 – Power System Stabilizer

The intent of Requirement R2 is to remove the previous requirement to log hours for PSS in service. In this ~~standard's~~ ~~Standard's~~ previous version, the logged hours were totaled quarterly to meet the 98% in-service requirement. Instead of documenting the number of hours excluded, this Requirement simplifies the process by allowing the Generator Operator to communicate to the Transmission Operator the circumstances that render the PSS unavailable to the Transmission Operator (such as component failure, maintenance, and testing).

Requirement R3

Nothing in this RSS should be construed to mandate the design criteria for the ~~equipment~~ used to produce the tuning output of the PSS. Rather, Requirement R3 is intended to address the design criteria for the ~~tuning output~~ of the PSS.

Unlike the language in Requirement R5 that looks *backward* to address units that were once operating but are no longer capable of operating, Requirement R3 looks *forward*, requiring that units be tuned to the specified parameters.

The PSS transfer function should compensate the phase characteristics of the generator, exciter, and power (GEP) system transfer function so the compensated transfer function ($(PSS(s) * GEP(s))$) has a phase characteristic of ± 30 degrees in the frequency range.

The GEP(s) transfer function is a theoretical transfer function, and its phase characteristic cannot be directly measured during field tests (only via simulation). Thus, the Requirement recognizes the practical approach of measuring the frequency response between voltage reference set point and terminal voltage (E_t/V_{ref}) and using the phase characteristic of such frequency response as being the phase characteristic of GEP(s). The phase characteristic of E_t/V_{ref} is a better approximation to the phase characteristic of GEP(s) when the frequency response E_t/V_{ref} is obtained with the generator synchronized to the grid at its minimum stable power output.

In an effort to allow for reasonable ~~wash out~~ ~~washout~~ time constants, the Requirement specifies 0.2 Hz as the applicable threshold. The 0.2 Hz threshold more closely aligns with the observed oscillation frequencies.

A properly tuned PSS should provide positive damping to the local mode of oscillation, which typically has a frequency higher than 1.0 Hz.

This Requirement modifies the requirement associated with the adjustment of the PSS gain. The standard no longer defines the PSS gain in terms of gain margin but instead requires the final PSS gain to be between 1/3 (10 dB) and 1/2 (6 dB) of the maximum practical gain that could be achieved during PSS commissioning. The maximum practical gain might be associated with the excessive noise or raised higher frequency oscillations in the closed loop response (exciter mode) or any other form if there is inadequate closed loop performance, as determined during PSS commissioning. It is now part of Measure M3 to show the field test results that led to the determination of the maximum practical gain.

Requirement R4

~~Requirement R4 requires a Generator Owner to install a PSS on new applicable units or when excitation systems are replaced or retrofitted on existing applicable units. This Requirement applies to new excitation systems and not to existing systems that do not have PSS. The Requirement also allows a reasonable amount of time for the commissioning of new PSS.~~

Requirement R5

~~Unlike the language in Requirement R3 that looks forward ~~to ensure~~ensuring that a unit is tuned, Requirement R5 looks *backward*. Specifically, the language in Requirement R5, “becoming incapable,” indicates the unit was previously capable of meeting the tuning requirements in Requirement R3, but is no longer capable. Restated, Requirement R5 addresses units that were previously working but are now no longer working.~~

~~The intent of Requirement R5 is to remove the “tiered” approach to PSS repair/replacement following a failure. A simple, streamlined approach to allow the Generator Owner sufficient time to repair or replace a broken PSS has been written. Consideration has been given for the need to procure parts or new equipment, schedule an equipment/unit outage, and install and test the repaired or replaced PSS. It is recognized that in some instances, it may require (1) replacement of an AVR, and (2) the existence of a PSS, or both the AVR and the PSS may need to be replaced to achieve a functioning system.~~

~~The 24 month time frame is sufficient to return a functional, operating PSS to service.~~

VAR-501-WECC-~~3.14~~ – Power System Stabilizer

*** FOR INFORMATIONAL PURPOSES ONLY ***

~~Enforcement Dates: Standard VAR 501 WECC 3 — Power System Stabilizer~~

United States

Standard	Requirement	Enforcement Date	Inactive Date
VAR 501 WECC 3	TBD	TBD	